

NetComm[®]
www.netcomm.com.au



Wireless Security Guide

(for Windows XP, Windows Vista, Mac OSx)

Wireless Security Guide

This guide will take you through the process of configuring, changing or checking the wireless security settings on an existing wireless network.

This guide **will not** assist you to setup a new wireless network. Please refer to the wireless setup document for your model available from the support section of the [NetComm](#)* or [Dynalink](#)** website.



Any changes to your wireless security settings will require you to reconfigure wirelessly connected devices to use the new security settings. Please ensure that you have your wireless setup guide handy for this.

* NetComm Support - <http://www.netcomm.com.au/support>

** Dynalink Support - <http://www.dynalink.co.nz/cms/index.php?page=how-to>

Step 1: Selecting a wireless security type:

There are a number of different types of wireless security to select from.

Before changing your settings, check the types of security available on your modem/router and then consult your wireless adapter manufacturer to ensure your wireless adapter is compatible with your chosen security type.

The most commonly used security types are:

- WEP (64bit or 128bit)
- WPA (Radius)
- WPA-PSK
- WPA2 (Radius)
- WPA2-PSK

The majority of wireless adapters should support one (or all) of the above security types.



You will be unable to utilise Radius server authentication without having a Radius server in place and configured on your network.

Step 2: Selecting a wireless security key:

Once you have chosen which wireless security type you want to use on your network, you will then need to create your wireless security key or wireless password.

Depending on the security type you choose, you will have the option of using either an ASCII or HEX format key.

ASCII refers to any letter or number you can see on your keyboard.

HEX refers to the letters A to F and the numbers 0 to 9.

You will need to ensure that your security key is the correct length. Your modem/router will display the required number of characters (letters and/or numbers) you need.



The default wireless key for most NetComm products is:

a1b2c3d4e5

Step 3: Setting up your wireless security:

Please ensure that your modem/router is connected to your computer using an ethernet cable before continuing.

1. Open your web browser and go to the address <http://192.168.1.1>, using admin as the username and password when prompted.
2. Select **"Wireless"** from the menu at the top of the page and then **"Security"** from the menu on the lefthandside.
3. If you have decided to use WEP and you would just like to change your current WEP network key, simply replace the key specified in the top box of the **"Encryption Key"** section and click **"Apply"**.

NetComm® HOME SETUP ADVANCED **WIRELESS** TOOLS STATUS EASYCONFIG HELP

Setup
Configuration
Multiple SSID
Security
Management
Log Out

Wireless Security

Select an SSID and its security level: wireless

☐ None ☒ WEP ☐ 802.1x ☐ WPA

☒ Enable WEP Wireless Security

Authentication Type: Open

Select Encryption Key Cipher

☒ A1 B2 C3 D4 E5 64 bits

☐ 64 bits

☐ 64 bits

☐ 64 bits

Enter 10, 26, or 58 hexadecimal digits for 64, 128 or 256 bit Encryption Keys respectively. e.g., AA AA AA AA AA for a key length of 64 bits.

Note: you must [Restart Access Point](#) for Wireless changes to take effect.

Apply Cancel

4. If you would like to select a different network security type instead, click the corresponding security type listed in the top section of the page.

The screenshot shows the NetComm Wireless Security configuration page. The left sidebar has a menu with 'Security' highlighted. The main content area is titled 'Wireless Security'. At the top, it says 'Select an SSID and its security level: wireless'. Below this, there are four radio buttons: 'None', 'WEP', '802.1x', and 'WPA'. The 'WPA' button is selected and highlighted with a red box. Below the radio buttons, there is a checkbox labeled 'Enable WEP Wireless Security' which is checked. Underneath, 'Authentication Type' is set to 'Open'. There are four 'Select' fields for 'Encryption Key', each with a radio button and a text input field. The first key is 'A1 B2 C3 D4 E5'. To the right of these keys are four 'Cipher' dropdown menus, all set to '64 bits'. At the bottom, there is a note: 'Note: you must Restart Access Point for Wireless changes to take effect.' and two buttons: 'Apply' and 'Cancel'.

5. After selecting your desired security type (we're using WPA2-PSK for the example), enter the wireless security key you would like to use into the "Pre-Shared Key:" section and click "Apply".

The screenshot shows the NetComm Wireless Security configuration page. The left sidebar has a menu with 'Security' highlighted. The main content area is titled 'Wireless Security'. At the top, it says 'Select an SSID and its security level: wireless'. Below this, there are four radio buttons: 'None', 'WEP', '802.1x', and 'WPA'. The 'WPA' button is selected. Under 'WPA', there are three sub-radio buttons: 'WPA', 'WPA2', and 'AnyWPA'. The 'WPA2' button is selected. Below these, there is a checkbox labeled 'Enable WPA2 Pre-authentication' which is unchecked. Underneath, 'Group Key Interval' is set to '3600'. To the right of this, there is a note: 'Note: This is shared by all WPA options.' Below this, there are three radio buttons: 'Radius Server', 'IP Address:', 'Port:', and 'Secret:'. The 'Pre-Shared Key' radio button is selected and highlighted with a red box. To the right of 'Pre-Shared Key', there is a 'PSK String' field with a text input field containing a series of dots. At the bottom, there is a note: 'Note: you must Restart Access Point for Wireless changes to take effect.' and two buttons: 'Apply' and 'Cancel'.

Any changes to your wireless security settings will require you to reconfigure any wirelessly connected devices to use the new security settings. This is done by removing any stored wireless settings and then reconnecting to your wireless network.

Please ensure you have your wireless setup guide handy for this.