

**NetComm**<sup>®</sup>  
*www.netcomm.com.au*



---

## **Wireless Security Guide**

(for Windows XP, Windows Vista, Mac OSx)

## **Wireless Security Guide**

This guide will take you through the process of configuring, changing or checking the wireless security settings on an existing wireless network.

This guide **will not** assist you to setup a new wireless network. Please refer to the wireless setup document for your model available from the support section of the [NetComm](#)\* or [Dynalink](#)\*\* website.



Any changes to your wireless security settings will require you to reconfigure wirelessly connected devices to use the new security settings. Please ensure that you have your wireless setup guide handy for this.

\* NetComm Support - <http://www.netcomm.com.au/support>

\*\* Dynalink Support - <http://www.dynalink.co.nz/cms/index.php?page=how-to>

## Step 1: Selecting a wireless security type:

There are a number of different types of wireless security to select from.

Before changing your settings, check the types of security available on your modem/router and then consult your wireless adapter manufacturer to ensure your wireless adapter is compatible with your chosen security type.

The most commonly used security types are:

- WEP (64bit or 128bit)
- WPA (Radius)
- WPA-PSK
- WPA2 (Radius)
- WPA2-PSK

The majority of wireless adapters should support one (or all) of the above security types.



You will be unable to utilise Radius server authentication without having a Radius server in place and configured on your network.

## Step 2: Selecting a wireless security key:

Once you have chosen which wireless security type you want to use on your network, you will then need to create your wireless security key or wireless password.

Depending on the security type you choose, you will have the option of using either an ASCII or HEX format key.

ASCII refers to any letter or number you can see on your keyboard.

HEX refers to the letters A to F and the numbers 0 to 9.

You will need to ensure that your security key is the correct length. Your modem/router will display the required number of characters (letters and/or numbers) you need.



The default wireless key for most NetComm products is:

**a1b2c3d4e5**

### Step 3: Setting up your wireless security:

**Please ensure that your modem/router is connected to your computer using an ethernet cable before continuing.**

1. Open your web browser and go to the address <http://192.168.1.1>, using admin as the username and password when prompted.
2. Click the **"Setting"** button in the **"Wireless"** section on the "OnePage Setup" screen.
3. Click **"Ok"** to enable Mandatory wireless security.

Host Name:  (Required by some ISPs)  
Domain Name:  (Required by some ISPs)  
Time Zone: (GMT+10:00) Canberra, Melbourne, Sydney  
Private IP Address: (MAC Address: 00-60-64-04-36-21)  
Device IP Address: 192 . 168 . 1 . 1  
Subnet Mask: 255.255.255.0

**Wireless** (MAC Address: 00-01-36-09-5C-C0)  
☒ Enable ☐ Disable  
SSID: wireless  
SSID Broadcast: ☒ Allow ☐ Disallow  
Channel: 9 (Domain: Europe / Australia)  
Wireless Security: ☒ Mandatory ☐ Disable **Setting**

4. After selecting your desired security type (we're using WPA2-PSK for the example), enter the wireless security key you would like to use into the **"WPA Shared Key:"** section and click **"Apply"**.

**Wireless Security:** WPA Pre-Shared Key  
**WPA Algorithms:** TKIP  
**WPA Shared Key:** ExampleKey  
**Group Key Renewal:** 3600 seconds  
**Apply** **Cancel**

Any changes to your wireless security settings will require you to reconfigure any wirelessly connected devices to use the new security settings. This is done by removing any stored wireless settings and then reconnecting to your wireless network.

Please ensure you have your wireless setup guide handy for this.