

*NetComm*<sup>®</sup>

 *Dynalink*

---

**Virgin Mobile 3G Modem Setup**

(3G18WV)

## 3G18WV Setup with a Virgin Mobile 3G Modem

1. Plug in your Virgin Mobile 3G modem into the 3G18WV.
2. Navigate to <http://192.168.20.1> in a web browser.
3. Enter "admin" as the system password and press the **Login** button.
4. Select the **Advanced** menu option.
5. Select Basic Settings > Network Setup.

NETCOMM LIBERTY™ SERIES  
3G Wireless N300 VoIP Router

ADMINISTRATOR'S MAIN MENU   Status   Wizard   Advanced   VoIP   Logout

BASIC SETTINGS   FORWARDING RULES   SECURITY SETTINGS   ADVANCED SETTINGS   TOOLBOX

Network Setup  
DHCP Server  
Wireless  
Change Password

LAN Setup	
Item	Setting
▶ LAN IP Address	192.168.20.1
▶ Subnet Mask	255.255.255.0
Internet Setup	
▶ Auto Failover status	Disable <input type="button" value="Setting"/>
▶ WAN Interface	3G connection
▶ Country	Australia
▶ Telecom	Virgin Mobile
▶ APN	virginbroadband (optional)
▶ PIN Code	(optional)
▶ Dialed Number	*99#
▶ Account	guest (optional)
▶ Password	***** (optional)
▶ Authentication	<input type="radio"/> Auto <input checked="" type="radio"/> PAP <input type="radio"/> CHAP
▶ Primary DNS	(optional)
▶ Secondary DNS	(optional)
▶ Prefer Service Mode	Auto Mode
▶ Connection Control	Auto Reconnect (always-on)
▶ Allowed Connection Time	<input checked="" type="radio"/> Always <input type="radio"/> By Schedule
▶ Roaming	<input type="checkbox"/> Enable

6. Set the **WAN Interface** to 3G Connection.
7. Set the **Country** to Australia.
8. Set **Telecom** to Virgin Mobile.
9. Enter "virginbroadband" as the **APN**.
10. Set the dialed number as "\*99#".
11. Set **Account** as "guest".
12. Set the **Password** also as "guest".
13. Set **Authentication** as "PAP".
14. Press the **Save** button.
15. Select the **Status** menu option and check the 3G modem connection status.

NETCOMM LIBERTY™ SERIES
NetComm®

## 3G Wireless N300 VoIP Router

ADMINISTRATOR'S MAIN MENU

[Status](#)
[Wizard](#)
[Advanced](#)
[VoIP](#)
[Logout](#)

System Status
[HELP]

Item	Status	Sidenote
IP Address	121.91.111.72	
Subnet Mask	255.255.255.255	
Gateway	10.64.64.64	
Domain Name Server	123.200.191.17 , 123.200.191.18	
Connection Time	00:02:12	

3G Modem Information

Item	Status	Sidenote
Card Info	E1762	
Link Status	Connected.	
Signal Strength	29%	
Network Name	Optus	