

## 3GT1WN Firmware Upgrade Instructions

**Purpose:** This document describes the steps necessary to perform a firmware upgrade on the 3GT1WN with the latest firmware (available on the NetComm website).  
To ensure a successful firmware upgrade please follow the below instructions.

**Firmware files location:**

To download the latest firmware of 3GT1WN, please click on the below link:

<http://www.netcomm.com.au/sm/firmware/3gT1wn>


Click on to the firmware file (example ntc3g1wt\_1.0.x.x.dat) and save it on your local PC.

**Warning:**


**Please ensure that your 3G USB Modem is not attached to 3GT1WN during the upgrade process as this may damage the 3GT1WN and void your warranty.**

**Upgrade Steps:**


- 1) Power on the 3GT1WN with the supplied power adapter.
- 2) Wait approximately 2 minutes for the device to finish starting up.
- 3) Press the reset button for 1 second and release on the side of the 3GT1WN.
- 4) Plug in one end of the supplied Yellow Ethernet cable to WAN/LAN port on the 3GT1WN.
- 5) Plug the other end of the Ethernet cable to the LAN port of your computer.
- 6) Please wait approximately 20 seconds.
- 7) Open your web browser.
- 8) Type in <http://192.168.20.1> on the address bar.




- 9) From the Login page, type in:  
Username: admin  
Password: admin  
Press **“Submit”** to log in.




- 10) Once you have logged in, mouseover **“Administration”** from the top menu and select **“Upload firmware”** from the drop down list.



- 11) Press the Browse button to select a firmware file to upgrade with.  
Administration > Upload Firmware




- 12) Locate and Select the latest firmware file downloaded from our NetComm website and press “Open”.



- 13) Next, press “Apply” to start the firmware upgrade.

Administration > Upload Firmware



- 14) Please note that it takes approximately 3 minutes for the 3GT1WN to upgrade. DO NOT turn off your 3GT1WN during the firmware upgrade process. Press “OK” to proceed.

Administration > Upload Firmware

**Upload Firmware**

This page allows you to upgrade your 3G Routers firmware. Click on Browse to locate the firmware file to be used for the upgrade. **Please note that it takes approximately 3 minutes for the firmware to be upgraded. DO NOT turn off your 3G Router during the firmware upgrade process.**

**Update Firmware**

Location:

**Message from webpage**

The router will download and upgrade the firmware. The whole upgrade procedure can take 3 minutes. The router shows the status page when the upgrade procedure finishes. Click OK to process

- 15) Once the firmware upgrade has been completed (the installation progress bar reaches 100%), please reconnect your 3GT1WN via LAN or Wireless.

All Status WAN PPPoE PPTP

System Info	
Firmware Version	1.0.17.0 (Jan 14 2010)
System Up Time	00 : 08 : 30
Battery Status	AC powered (charging)
Operation Mode	Gateway Mode
Local Network	
Local IP Address	192.168.20.1
Local Netmask	255.255.255.0

- 16) To ensure the firmware upgrade has been successful, please check the firmware version on the system status page as shown below.

All Status WAN PPPoE PPTP

System Info	
Firmware Version	1.0.17.0 (Jan 14 2010)
System Up Time	00 : 08 : 30
Battery Status	AC powered (charging)
Operation Mode	Gateway Mode
Local Network	
Local IP Address	192.168.20.1
Local Netmask	255.255.255.0