

3GT1WN Firmware Upgrade Instructions

 Purpose:
 This document describes the steps necessary to perform a firmware upgrade on the 3GT1WN with the latest firmware (available on the NetComm website).

To ensure a successful firmware upgrade please follow the below instructions.

Firmware files location:

To download the latest firmware of 3GT1WN, please click on the below link:

http://www.netcomm.com.au/sm/firmware/3gT1wn

Click on to the firmware file (example ntc3g1wt_1.0.x.x.dat) and save it on your local PC.

Warning:

Please ensure that your 3G USB Modem is not attached to 3GT1WN during the upgrade process as this may damage the 3GT1WN and void your warranty.

Upgrade Steps:

- 1) Power on the 3GT1WN with the supplied power adapter.
- 2) Wait approximately 2 minutes for the device to finish starting up.
- 3) Press the reset button for 1 second and release on the side of the 3GT1WN.
- 4) Plug in one end of the supplied Yellow Ethernet cable to WAN/LAN port on the 3GT1WN.
- 5) Plug the other end of the Ethernet cable to the LAN port of your computer.
- 6) Please wait approximately 20 seconds.
- 7) Open your web browser.
- 8) Type in <u>http://192.168.20.1</u> on the address bar.

🖉 system	Statu	us - Micros	soft Int	ernet	Explorer pr	ovided by NetComm	J
G	2	http://192.1	68.20.1/				
File Edit	View	Favorites	Tools	Help			
🚖 Favorites		🏉 Sugge:	sted Site:	s 🕶 🥫	Free Hotmail	🔊 NetComm Intranet	🖉 NetComm WebMail
🥖 🖉 system S	Status						



 9) From the Login page, type in: Username: admin
 Password: admin
 Press "Submit" to log in.

Status	Login	LUg				
Login						
Login						
Login						
			_			
	User Name:	admin				
	Password:	••••				
			Submit	Clear		

10) Once you have logged in, mouseover "**Administration**" from the top menu and select "**Upload firmware**" from the drop down list.

Status		► Internet S	ettings	► Wireless Settings	▶ Firewall	 Administration 	
All Status	WAN	PPPoE	PPTP			Management Upload Firmware	

11) Press the Browse button to select a firmware file to upgrade with. Administration > Upload Firmware

Upload Firmware				
This page allows you to upgrade your 3G Routers firmware. Click on Browse to locate the firmware file to be used for the upgrade.Please note that it takes approximately 3 minutes for the firmware to be upgraded. DO NOT turn off your 3G Router during the firmware upgrade process.				
Update Firmware				
Location:	Browse			
	Apply			



12) Locate and Select the latest firmware file downloaded from our NetComm website and press "Open".

Location:		C:\Documents and Setti Browse				
				1 l]		
Choose File to l	Upload					? 🗙
Look in:	irmware 🔁		•	G 🦻	۳ 🍽	
My Recent Documents Desktop My Documents My Computer	ntc3g1wt_1	.0.x.x.dat				
My Network	File name:	ntc3q1wt 1.0 x x dat			•	Open
Places	en z.				- 1	Count
	Files of type:	All Files (^.^)			-	Lancel

13) Next, press "**Apply**" to start the firmware upgrade. Administration > Upload Firmware

Upload Firmware					
This page allows you to upgra note that it takes approximatel process.	This page allows you to upgrade your 3G Routers firmware. Click on Browse to locate the firmware file to be used for the upgrade.Please note that it takes approximately 3 minutes for the firmware to be upgraded. DO NOT turn off your 3G Router during the firmware upgrade process.				
Update Firmware					
Location:	are\ntc3g1wt_1.0.xx.dat Browse				
	Apply				



14) Please note that it takes approximately 3 minutes for the 3GT1WN to upgrade. DO NOT turn off your 3GT1WN during the firmware upgrade process. Press "**OK**" to proceed.

Administration > Upload Firmw	rare
Upload Firmware	
This page allows you to upgra note that it takes approximately process.	de your 3G Routers firmware. Click on Browse to locate the firmware file to be used for the upgrade.Please y 3 minutes for the firmware to be upgraded. DO NOT turn off your 3G Router during the firmware upgrade
Update Firmware	
Location:	are\ntc3g1wt_1.0.x.x.dat Browse
	Apply
- Nessage from webpage	
The router will download an procedure finishes. Click O	nd upgrade the firmware. The whole upgrade procedure can take 3 minutes. The router shows the status page when the upgra K to process

15) Once the firmware upgrade has been completed (the installation progress bar reaches 100%), please reconnect your 3GT1WN via LAN or Wireless.
 All Status WAN PPPOE PPTP

System Info			
Firmware Version	1.0.17.0 (Jan 14 2010)		
System Up Time	00:08:30		
Battery Status	AC powered (charging)		
Operation Mode	Gateway Mode		
Local Network			
Local IP Address	192.168.20.1		
Local Netmask	255.255.255.0		

16) To ensure the firmware upgrade has been successful, please check the firmware version on the system status page as shown below.

All Status WAN PPPoE	PPTP			
📕 System Info				
Firmware Version		1.0.17.0 (Jan 14 2010)		
System Up Time		00:08:30		
Battery Status		AC powered (charging)		
Operation Mode		Gateway Mode		
Local Network				