



Let's get started >

To connect to the Internet

1. Install

- Connect the **yellow Ethernet cable** to one of the 4 yellow Ethernet ports found at the back of the modem. Connect the other end of the cable to an available Ethernet port on your computer.
- Connect the **gray telephone cable** to the gray port on the back of the modem and connect the other end to the telephone port on your wall*.
- Connect the **power cord** to the back of the modem and insert the plug pack into a power point. Then turn ON the power button on the back of the modem.

2. Configure

- Insert the CD**, when the CD loads click on **Setup my Modem**.
- Click on **NB7 Series Wizard**.
- Follow the steps shown.

3. Enjoy!

If you have lost the CD please turn over for instructions on how to manually set up your modem.

* Please note, to ensure you receive the best performance from your modem you must use a filter on all telephone devices using the same line. (Recommended NetComm EM1550 ADSL2+ Line Filter)



NOTE: Only follow these instructions if you have lost your Install CD, if you have your CD please turn over for instructions.

1. Install

- Connect the **yellow Ethernet cable** to one of the 4 yellow Ethernet ports found at the back of the modem. Connect the other end of the cable to an available Ethernet port on your computer.
- Connect the **gray telephone cable** to the gray port on the back of the modem and connect the other end to the telephone port on your wall*.
- Connect the **power cord** to the back of the modem and insert the plug pack into a power point. Then power ON the modem.

2. Configure

- Open a web browser** and in the address bar type **192.168.1.1**
- When it asks for a username and password enter: **Username: admin, Password: admin.**
- On the left hand side of the screen click on **Quick Setup link.**
- In the PPP Username box enter your **Username** (This will be supplied by your ISP).
- In the PPP Password box enter your **Password** (This will be supplied by your ISP).
- Click on the button named **Save/Reboot.**

3. Check

- Once the modem has rebooted, open up your web browser and type **www.netcomm.com.au** into your browsers address bar, if the page loads you are connected to the Internet!

4. Enjoy!